



The INVERTERS RANGE

PURE SINE CONVERTERS



PURE SINE

Pure Sine signal suitable for use in sensitive and demanding devices.



AUTOMATIC

Automatically switches the power supply to 220V when plugged in.



AUTO WATCH

Earth leakage circuit breaker with automatic restart.



ERGONOMIC

In addition to being quiet, the weight and volume are optimised.

EZA POWER PUR-SINUS CONVERTERS ARE ESPECIALLY DESIGNED AND ADAPTED TO THE SPECIFIC NEEDS OF RECREATIONAL VEHICLES.

Pure-Sinus converters are especially designed and adapted to the specific needs of the Recreational Vehicle industry. They are safe to operate, capable of absorbing high currents and withstanding variations in load during use. They have a current quality equal to or better than a domestic socket.

The use is intended for inductive electrical appliances (DIY equipment, pumps, motors, refrigerators, neon compressors,...), appliances with electronics that are sensitive to a perfect current quality such as: (refrigerators, freezers, microwaves, computers, washing machines, TVs, medical equipment, smartphone chargers and electrically assisted bicycles) and / or appliances that require a high starting power (air conditioner, espresso machine, hair dryer, DIY equipment, drill, ...).

INTELLIGENT

Thanks to the MPS system (Mains Priority Function) the 2000W and 3000W inverters automatically switch over when the vehicle connects to the 220V mains (e.g. car park, camping site, at home...) to save the auxiliary battery. When the vehicle disconnects from the mains, the inverter switches back to the battery in a few milliseconds to continue to supply the consumer. Included: Low voltage safety device to protect batteries against deep discharge, specific Recreational Vehicle wiring included and USB output on the whole range. Electronic protection against: reverse polarity, short circuit, overheating.

COMPATIBILITY

Compatible with all battery types including Lithium LiFePo4. Remote control included for remote control and shutdown of the inverter to eliminate residual or passive power consumption when the unit is powered. Reinforced mounting brackets for floor or wall installation. Suitable cables for safe use and installation.



The INVERTERS RANGE

PURE SINE CONVERTERS

PRODUCT FEATURES	300W	500W	1000W	2000W	3000W
	466373	466381	466387	466391	466395
POWER RATING	300W	500W	1000W	2000W	3000W
PEAK POWER (3sec.)	600W	1000W	2000W	4000W	6000W
TECHNOLOGY	PURE SINUSOIDAL WAVE				
INPUT VOLTAGE DC	11-16V				
OUTPUT VOLTAGE AC	230V - 50Hz				
AC SOCKET	FR CHILD SAFETY				
NO-LOAD CONSUMPTION	<0.50A	<0.60A	<0.80A	<0.95A	<1.3A
PRIORITY MPS SECTOR	NON		OUI		
LOW VOLTAGE SAFETY	YES, 11V				
HIGH VOLTAGE SAFETY	YES, 16V				
REVERSE POLARITY SAFETY DEVICE	YES				
SHORT-CIRCUIT SAFETY	YES				
OVERHEATING SAFETY DEVICE	YES				
USB SOCKET OUTPUT	YES / 1USB 5V,2.1A				
MODE OF COMMUNICATION	LED REMOTE CONTROL (5M)				
PERMITTED POSITION/FIXING	Horizontal and vertical				
AC CONNECTICAL	-		Cable 230V supplied / 1m	Cable 230V supplied / 1m	Cable 230V supplied / 1m
DC CONNECTICAL	Cables supplied 6mm ² /50cmx3	Cables supplied 10mm ² /50cm x 2	Cables supplied 16mm ² /50cm x 2	Cables supplied 25mm ² /50cm x 2	Cables supplied 35mm ² /50cm x 2
PROTECTIVE FUSE	YES, EXTERNAL				
DIMENSIONS IN MM PRODUCT (L x W x H)	180*150*70	180*150*70	350*150*70	380*220*90	410*220*150
NET WEIGHT	1,5KG	2KG	3KG	5KG	8KG
DELIVERED WITH	MANUAL + CABLE CERTIFICATIONS				
CERTIFICATIONS, APPROVALS	R10 + CE (EMC - LVD) + RoHS				
GUARANTEE	2 YEARS				

REFERENCING & LOGISTICS DATA	300W	500W	1000W	2000W	3000W
	466373	466381	466387	466391	466395
EAN CODE	3700628245544	3700628245582	3700628245629	3700628245667	3700628245704
CUSTOMS CODE	850440908080	850440908080	850440908080	850440908080	850440908080
SUPPLIER ORIGIN	CHINA				
DIMENSIONS IN MM PACKAGED PRODUCT (L x W x H)	320*200*135	320*200*135	460*200*135	490*290*170	540*330*220
PACKAGING	COLOR PACKAGING				
GROSS WEIGHT (KG)	1,5KG	2	3	5	8
QTY CARBOARD	1	1	1	1	1
QTY / MASTER CARDBOARD / GROSS WEIGHT	6 / 14KG	6 / 18KG	4 / 17KG	2 / 14KG	1 / 11KG
QTY PALLET / GROSS WEIGHT	168 / 267KG	168 / 351KG	112 / 351KG	68 / 355KG	42 / 351KG
QTY CT / 20	2615	2615	1955	1035	490
QTY CT / 40 HC	6350	6350	4750	2520	1190

To access to the digital version, scan this QR Code.



Need advice ?

Contact the EZA Hotline on **04 68 44 16 24**



All our products are **2 Year Warranty**



The website **www.eza.fr**



The INVERTERS RANGE

PURE SINE CONVERTERS



PURE SINE

Pure Sine signal suitable for use in sensitive and demanding devices.



AUTOMATIC

Automatically switches the power supply to 220V when plugged in.



AUTO WATCH

Earth leakage circuit breaker with automatic restart.



ERGONOMIC

In addition to being quiet, the weight and volume are optimised.

EZA POWER PUR-SINUS CONVERTERS ARE ESPECIALLY DESIGNED AND ADAPTED TO THE SPECIFIC NEEDS OF RECREATIONAL VEHICLES.

Pure-Sinus converters are especially designed and adapted to the specific needs of the Recreational Vehicle industry. They are safe to operate, capable of absorbing high currents and withstanding variations in load during use. They have a current quality equal to or better than a domestic socket.

The use is intended for inductive electrical appliances (DIY equipment, pumps, motors, refrigerators, neon compressors,...), appliances with electronics that are sensitive to a perfect current quality such as: (refrigerators, freezers, microwaves, computers, washing machines, TVs, medical equipment, smartphone chargers and electrically assisted bicycles) and / or appliances that require a high starting power (air conditioner, espresso machine, hair dryer, DIY equipment, drill, ...).

INTELLIGENT

Thanks to the MPS system (Mains Priority Function) the 2000W and 3000W inverters automatically switch over when the vehicle connects to the 220V mains (e.g. car park, camping site, at home...) to save the auxiliary battery. When the vehicle disconnects from the mains, the inverter switches back to the battery in a few milliseconds to continue to supply the consumer. Included: Low voltage safety device to protect batteries from deep discharge, specific Recreational Vehicle wiring included and USB output throughout the range. Electronic protection against: reverse polarity, short circuit, overheating.

COMPATIBILITY

Compatible with all battery types including Lithium LiFePo4. Remote control included for remote control and shutdown of the inverter to eliminate residual or passive power consumption when the unit is powered. Reinforced mounting brackets for floor or wall installation. Suitable cables for safe use and installation.



The INVERTERS RANGE

PURE SINE CONVERTERS

PRODUCT FEATURES	300W	500W	1000W	2000W	3000W
	466375	466385	466389	466393	466397
POWER RATING	300W	500W	1000W	2000W	3000W
PEAK POWER (3sec.)	600W	1000W	2000W	4000W	6000W
TECHNOLOGY	PURE SINUSOIDAL WAVE				
INPUT VOLTAGE DC	11-16V				
OUTPUT VOLTAGE AC	230V - 50Hz				
AC SOCKET	UK G TYPE				
NO-LOAD CONSUMPTION	<0.50A	<0.60A	<0.80A	<0.95A	<1.3A
PRIORITY MPS SECTOR	NON		OUI		
LOW VOLTAGE SAFETY	YES, 11V				
HIGH VOLTAGE SAFETY	YES, 16V				
REVERSE POLARITY SAFETY DEVICE	YES				
SHORT-CIRCUIT SAFETY	YES				
OVERHEATING SAFETY DEVICE	YES				
USB SOCKET OUTPUT	YES / 1USB 5V,2.1A				
MODE DE COMMUNICATION	LED REMOTE CONTROL (5M)				
PERMITTED POSITION/FIXING	Horizontal and vertical				
AC CONNECTICAL	-		Cable 230V supplied / 1m	Cable 230V supplied / 1m	Cable 230V supplied / 1m
DC CONNECTICAL	Cables supplied 6mm ² /50cmx3	Cables supplied 10mm ² /50cm x 2	Cables supplied 16mm ² /50cm x 2	Cables supplied 25mm ² /50cm x 2	Cables supplied 35mm ² /50cm x 2
PROTECTIVE FUSE	YES, EXTERNAL				
DIMENSIONS IN MM PRODUCT (L x W x H)	180*150*70	180*150*70	350*150*70	380*220*90	410*220*150
NET WEIGHT	1,5KG	2KG	3KG	5KG	8KG
DELIVERED WITH	MANUAL + CABLES				
CERTIFICATIONS, APPROVALS	R10 + CE (EMC - LVD) + RoHS				
GUARANTEE	2 YEARS				

REFERENCING & LOGISTICS DATA	300W	500W	1000W	2000W	3000W
	466375	466385	466389	466393	466397
EAN CODE	3700628245544	3700628245582	3700628245629	3700628245667	3700628245704
CUSTOMS CODE	850440908080	850440908080	850440908080	850440908080	850440908080
SUPPLIER ORIGIN	CHINA				
DIMENSIONS IN MM PACKAGED PRODUCT (L x W x H)	320*200*135	320*200*135	460*200*135	490*290*170	540*330*220
PACKAGING	COLOR PACKAGING				
GROSS WEIGHT (KG)	1,5KG	2	3	5	8
QTY CARBOARD	1	1	1	1	1
QTY / MASTER CARDBOARD / GROSS WEIGHT	6 / 14KG	6 / 18KG	4 / 17KG	2 / 14KG	1 / 11KG
QTY PALLET / GROSS WEIGHT	168 / 267KG	168 / 351KG	112 / 351KG	68 / 355KG	42 / 351KG
QTY CT / 20	2615	2615	1955	1035	490
QTY CT / 40 HC	6350	6350	4750	2520	1190

To access to the digital version, scan this QR Code.



Need advice ?

Contact the EZA Hotline on **04 68 44 16 24**



All our products are **2 Year Warranty**



The website **www.eza.fr**



The INVERTERS RANGE

PURE SINE CONVERTERS



PURE SINE

Pure Sine signal suitable for use in sensitive and demanding devices.



AUTOMATIC

Automatically switches the power supply to 220V when plugged in.



AUTO WATCH

Earth leakage circuit breaker with automatic restart.



ERGONOMIC

In addition to being quiet, the weight and volume are optimised.

EZA POWER PUR-SINUS CONVERTERS ARE ESPECIALLY DESIGNED AND ADAPTED TO THE SPECIFIC NEEDS OF RECREATIONAL VEHICLES.

Pure-Sinus converters are especially designed and adapted to the specific needs of the Recreational Vehicle industry. They are safe to operate, capable of absorbing high currents and withstanding variations in load during use. They have a current quality equal to or better than a domestic socket.

The use is intended for inductive electrical appliances (DIY equipment, pumps, motors, refrigerators, neon compressors,...), appliances with electronics that are sensitive to a perfect current quality such as: (refrigerators, freezers, microwaves, computers, washing machines, TVs, medical equipment, smartphone chargers and electrically assisted bicycles) and / or appliances that require a high starting power (air conditioner, espresso machine, hair dryer, DIY equipment, drill, ...).

INTELLIGENT

Thanks to the MPS system (Mains Priority Function) the 2000W and 3000W inverters automatically switch over when the vehicle connects to the 220V mains (e.g. car park, camping site, at home...) to save the auxiliary battery. When the vehicle disconnects from the mains, the inverter switches back to the battery in a few milliseconds to continue to supply the electrical consumer. Included: Low voltage safety device to protect batteries against deep discharge, specific Recreational Vehicle wiring included and USB output on the whole range. Electronic protection against: reverse polarity, short circuit, overheating.

COMPATIBILITY

Compatible with all battery types including Lithium LiFePo4. Remote control included for remote control and shutdown of the inverter to eliminate residual or passive power consumption when the unit is powered. Reinforced mounting brackets for floor or wall installation. Suitable cables for safe use and installation.



The INVERTERS RANGE

PURE SINE CONVERTERS

PRODUCT FEATURES	300W	500W	1000W	2000W	3000W
	466376	466386	466390	466394	466398
POWER RATING	300W	500W	1000W	2000W	3000W
PEAK POWER (3sec.)	600W	1000W	2000W	4000W	6000W
TECHNOLOGY	PURE SINUSOIDAL WAVE				
INPUT VOLTAGE DC	11-16V				
OUTPUT VOLTAGE AC	230V - 50Hz				
AC SOCKET	SCHUKO				
NO-LOAD CONSUMPTION	<0.50A	<0.60A	<0.80A	<0.95A	<1.3A
PRIORITY MPS SECTOR	NON		OUI		
LOW VOLTAGE SAFETY				YES, 11V	
HIGH VOLTAGE SAFETY				YES, 16V	
REVERSE POLARITY SAFETY DEVICE				YES	
SHORT-CIRCUIT SAFETY				YES	
OVERHEATING SAFETY DEVICE				YES	
USB SOCKET OUTPUT	YES / 1USB 5V,2.1A				
MODE OF COMMUNICATION	LED REMOTE CONTROL (5M)				
PERMITTED POSITION/FIXING	Horizontal and vertical				
AC CONNECTICAL			Cable 230V supplied / 1m	Cable 230V supplied / 1m	Cable 230V supplied / 1m
DC CONNECTICAL	Cables supplied 6mm ² /50cmx3	Cables supplied 10mm ² /50cm x 2	Cables supplied 16mm ² /50cm x 2	Cables supplied 25mm ² /50cm x 2	Cables supplied 35mm ² /50cm x 2
PROTECTIVE FUSE	YES, EXTERNAL				
DIMENSIONS IN MM PRODUCT (L x W x H)	180*150*70	180*150*70	350*150*70	380*220*90	410*220*150
NET WEIGHT	1,5KG	2KG	3KG	5KG	8KG
DELIVERED WITH	MANUAL + CABLE CERTIFICATIONS				
CERTIFICATIONS, APPROVALS	R10 + CE (EMC - LVD) + RoHS				
GUARANTEE	2 YEARS				

REFERENCING & LOGISTICS DATA	300W	500W	1000W	2000W	3000W
	466376	466386	466390	466394	466398
EAN CODE	3700628245544	3700628245582	3700628245629	3700628245667	3700628245704
CUSTOMS CODE	850440908080	850440908080	850440908080	850440908080	850440908080
SUPPLIER ORIGIN	CHINA				
DIMENSIONS IN MM PACKAGED PRODUCT (L x W x H)	320*200*135	320*200*135	460*200*135	490*290*170	540*330*220
PACKAGING	COLOR PACKAGING				
GROSS WEIGHT (KG)	1,5KG	2	3	5	8
QTY CARBOARD	1	1	1	1	1
QTY / MASTER CARDBOARD / GROSS WEIGHT	6 / 14KG	6 / 18KG	4 / 17KG	2 / 14KG	1 / 11KG
QTY PALLET / GROSS WEIGHT	168 / 267KG	168 / 351KG	112 / 351KG	68 / 355KG	42 / 351KG
QTY CT / 20	2615	2615	1955	1035	490
QTY CT / 40 HC	6350	6350	4750	2520	1190

To access to the digital version, scan this QR Code.



Need advice ?

Contact the EZA Hotline on **04 68 44 16 24**



All our products are **2 Year Warranty**



The website **www.eza.fr**